



GD-3000 Flammable Gas-Leak Detector

- Audible and Visual Annunciation
- Detects: LAG, LPG, CH₄, Methane, Butane, Flammable Gas
- Catalytic Combustion Sensor

Specifications

Name	Portable gas detector		
Function	Detecting the gas leakage and absorbing static electricity		
Power consumption	DC 200mA	Battery size	1.5V x 2(AAA Size)
Detectable gas	LNG, LPG	Temperature	-10°C~50°C
Humidity	95%RH or lower	Duration	About 4 hours continuously

Size(HxWxD): 164mm x 21mm

Weight: 25g

Accessories :

2 x "AAA" Alkaline Batteries and clamshell.